

## AUTOMATIC RELAY TESTER

### FEATURES:

- Test report printout from the instrument on a built in thermal printer.
- Portable unit.
- Designed for easy and safe test of simple relays
- Large LCD display
- CT test featured are incorporated



### MAIN SPECIFICATION:

	<b>AC Current (I1)</b>
<b>Range</b>	0 to 1 - 10 - 100 A variable.
<b>Power</b>	500VA(10A), 800VA(100A)
<b>Accuracy</b>	±1.5%, ± 2 counts.
	<b>AC Voltage (U1)</b>
<b>Range</b>	10-500V
<b>Power (500V)</b>	500 VA
<b>Accuracy</b>	±1.0%, ± 2 counts.
	<b>DC Voltage</b>
<b>Range</b>	10 - 300 V
<b>Power (300V)</b>	600 W
<b>Accuracy</b>	± 0.5 %, ± 2 counts.
	<b>Auxiliary DC</b>
<b>Range</b>	20-240V
<b>Power</b>	250 VA
<b>Accuracy</b>	±1.0%, ± 2 counts.
	<b>Resolution / output</b>
<b>Number</b>	1
<b>Type</b>	Potential free relay contact
	<b>Voltmeter</b>
<b>Range</b>	0-600V ac/dc
<b>Accuracy</b>	1.00%
	<b>Ammeter</b>
<b>Range</b>	100 A AC
<b>Accuracy</b>	1.00%

### AJIT ELECTRONICS COMPANY

Registered Office : B /301, Vasant Vihar Annex, Gandhi Nagar, Dombivli (East) - 421 204, Dist - Thane, Maharashtra, INDIA.

Tel. No: 0251 - 2871652 Fax No.: 0251 - 2871652